

# Assignment 3

**P1:** In the on-off keying version of an ASK system, symbol 1 is represented by transmitting a sinusoidal carrier of amplitude  $\sqrt{2E_b/T_b}$ , where  $E_b$  is the signal energy per bit and  $T_b$  is the bit duration. Symbol 0 is represented by switching off the carrier. Assume that symbols 1 and 0 occur with equal probability.

For an AWGN channel, determine the average probability of error for this ASK system under the following scenarios:

- Coherent reception.
- Noncoherent reception, operating with a large value of bit energy-to-noise spectral density ratio  $E_b/N_0$ .

*Note:* When  $x$  is large, the modified Bessel function of the first kind of zero order may be approximated as follows (see Appendix 3):

$$I_0(x) \approx \frac{\exp(x)}{\sqrt{2\pi x}}$$

**P2:** A PSK signal is applied to a correlator supplied with a phase reference that lies within  $\varphi$  radians of the exact carrier phase. Determine the effect of the phase error  $\varphi$  on the average probability of error of the system.

**P3:** The signal component of a coherent PSK system is defined by

$$s(t) = A_c k \sin(2\pi f_c t) \pm A_c \sqrt{1 - k^2} \cos(2\pi f_c t)$$

where  $0 \leq t \leq T_b$ , and the plus sign corresponds to symbol 1 and the minus sign corresponds to symbol 0. The first term represents a carrier component included for the purpose of synchronizing the receiver to the transmitter.

- Draw a signal-space diagram for the scheme described here; what observations can you make about this diagram?
- Show that, in the presence of additive white Gaussian noise of zero mean and power spectral density  $N_0/2$ , the average probability of error is

$$P_e = \frac{1}{2} \operatorname{erfc} \left( \sqrt{\frac{E_b}{N_0} (1 - k^2)} \right)$$

where

$$E_b = \frac{1}{2} A_c^2 T_b$$

- Suppose that 10 percent of the transmitted signal power is allocated to the carrier component. Determine the  $E_b/N_0$  required to realize a probability of error equal to  $10^{-4}$ .
- Compare this value of  $E_b/N_0$  with that required for a conventional PSK system with the same probability of error.

**P4:** - Determine the transmission bandwidth reduction and average signal energy of 256-QAM, compared to 64-QAM.

**P5:** - Two passband data transmission systems are to be compared. One system uses 16-PSK, and the other uses 16-QAM. Both systems are required to produce an average probability of symbol error equal to  $10^{-3}$ . Compare the signal-to-noise ratio requirements of these two systems.

P6:

An FSK system transmits binary data at the rate of  $2.5 \times 10^6$  bits per second. During the course of transmission, white Gaussian noise of zero mean and power spectral density  $10^{-20}$  W/Hz is added to the signal. In the absence of noise, the amplitude of the received sinusoidal wave for digit 1 or 0 is 1 mV. Determine the average probability of symbol error for the following system configurations:

- (a) Coherent binary FSK
- (b) Coherent MSK
- (c) Noncoherent binary FSK

P7:

- (a) In a coherent FSK system, the signals  $s_1(t)$  and  $s_2(t)$  representing symbols 1 and 0, respectively, are defined by

$$s_1(t), s_2(t) = A_c \cos \left[ 2\pi \left( f_c \pm \frac{\Delta f}{2} \right) t \right], \quad 0 \leq t \leq T_b$$

Assuming that  $f_c > \Delta f$ , show that the correlation coefficient of the signals  $s_1(t)$  and  $s_2(t)$  is approximately given by

$$\rho = \frac{\int_0^{T_b} s_1(t)s_2(t) dt}{\int_0^{T_b} s_1^2(t) dt} \approx \text{sinc}(2\Delta f T_b)$$

- (b) What is the minimum value of frequency shift  $\Delta f$  for which the signals  $s_1(t)$  and  $s_2(t)$  are orthogonal?
- (c) What is the value of  $\Delta f$  that minimizes the average probability of symbol error?
- (d) For the value of  $\Delta f$  obtained in part (c), determine the increase in  $E_b/N_0$  required so that this coherent FSK system has the same noise performance as a coherent binary PSK system.

P8:

- (a) Sketch the waveforms of the in-phase and quadrature components of the MSK signal in response to the input binary sequence 1100100010.
- (b) Sketch the MSK waveform itself for the binary sequence specified in part (a).